FOX LUX
EMERGENCY LIGHTING

FXSD02S-3-O-3-BLK SELF-TEST* LED EMERGENCY DOWNLIGHT SURFACE



Technical Data

Model Variant	FXSD02S-3-O-3
Rated Supply Voltage	220-240V AC
Mains Frequency	50 / 60 Hz
Max. Power Consumption	5W
Standby Power	< 0.5W
Emergency Output Power	3W nominal
Lumen Output	330 lumens
Rated Emergency Duration	3 hours
Battery Charge Time	< 16 hours
Operating Temperature	0 to 40°C
Insulation Class	Class II
Ingress Protection	IP 20
Impact Protection	IK 06
Dimensions (L x W x H)	150Ø x 40mm
Battery Compatibility	2 x 18650 Li-ion 3.6V 5.0Ah
Battery Code	FXC3.6-5000-B80
LED Configuration	TD 5050
Lens Type / Beam Angle	Open area / 140°

IMPORTANT NOTE: This self-test luminaire is configured to manual test mode by default.
If self-test mode is required, it should be activated via remote control (ref.: REM-E1).
With this feature enabled, functional and duration tests are conducted according to BS EN 50172:2004
This product is compatible with our infrared remote control. See product REM-E1 for more details.
To optimise long-term battery performance, the luminaire will operate for 3 hours before automatically shutting down.
The battery must be recharged within 6 months of full discharge.
When the rated operational time is no longer reached after a full recharge, the battery must be replaced.

hello@fox-lux.co.uk
www.fox-lux.co.uk
+44(0)1543 396400
Fox Lux Ltd., Unit 17 Britannia Way, Lichfield WS14 9UY

FOX LUX
EMERGENCY LIGHTING

FXSD02S-3-O-3-BLK SELF-TEST* LED EMERGENCY SURFACE DOWNLIGHT

Indicator LED Status

GREEN LED	RED LED	STATUS
On	Off	Standby
Slow Flash	Off	Charging
Fast Flash	Off	Function test or duration test in progress
Off	On	Battery disconnected / Duration test failed
Slow Flash	Slow Flash	Battery temperature out of operational range
Off	Slow Flash	Light source fault

NOTE: “Slow Flash” = 1 flash per second. “Fast Flash” = 2 Flashes per second

Installation Guide

1 Remove Product from Packaging



2 Remove Mounting Base



3 Install Mounting Base

Use the installation holes to mount the base.



4 Connect to Power Supply

Terminate mains supply as indicated.

Terminals suitable for cable size
0.75 to 1.5 mm2
Insulation strip length of 8+1mm

N- neutral (Blue)
L- Live (Brown)



5 Complete Labels

FOX LUX
Part No.
X | 1 | | 180
Commissioning Date:__ /__ /____

FOX LUX
Part No.
Date Of Manufacture MM/YYYY
Commissioning Date:__ /__ /____

6 Attach Body to Base

Line up the catches and clip the front cover into place.



7 Self-test

OPTIONAL: Set additonal features via remote.



hello@fox-lux.co.uk
www.fox-lux.co.uk
+44(0)1543 396400
Fox Lux Ltd., Unit 17 Britannia Way, Lichfield WS14 9UY